


User Manual

GT-346F Analog Input Module

16 ch, 0 - 5 V / 1 - 5 V / 0 - 10 V, 16 bit resolution, 20 pt connector

Doc ID: 78507
2025-02-20



The information in this document is subject to change without notice and is provided as available at the time of printing. Beijer Electronics AB reserves the right to change any information without updating this publication. Beijer Electronics AB assumes no responsibility for any errors that may appear in this document. All examples in this document are only intended to improve understanding of the functionality and handling of the equipment. Beijer Electronics AB cannot assume any liability if these examples are used in real applications. In view of the wide range of applications for this software, users must acquire sufficient knowledge themselves in order to ensure that it is correctly used in their specific application. Persons responsible for the application and the equipment must themselves ensure that each application is in compliance with all relevant requirements, standards, and legislation in respect to configuration and safety. Beijer Electronics AB will accept no liability for any damage incurred during the installation or use of equipment mentioned in this document. Beijer Electronics AB prohibits all modification, changes, or conversion of the equipment.

Head Office

Beijer Electronics AB

Box 426

201 24 Malmö, Sweden

www.beijerelectronics.com / +46 40 358600

Table of Contents

1. About This Manual	5
1.1. Symbols Used in This Manual	5
2. Safety	6
2.1. Product Certifications	6
2.2. General Safety Requirements	6
3. About the G-series System	7
3.1. IO Process Data Mapping	8
4. Specifications	9
4.1. Environmental Specifications	9
4.2. General Specification	10
4.3. Input Specifications	11
5. Wiring Diagram	12
6. LED Indicator	14
6.1. LED Channel Status	14
7. Data value / Voltage	15
8. Mapping Data into the Image Table	17
9. Parameter Data	19
10. Hardware Setup	20
10.1. Space Requirements	20
10.2. Mount Module to DIN Rail	21
10.3. Field Power and Data Pins	23

1. About This Manual

This manual contains information on the software and hardware features of the Beijer Electronics GT-346F Analog Input Module. It provides in-depth specifications, guidance on installation, setup, and usage of the product.

1.1. Symbols Used in This Manual

This publication includes Warning, Caution, Note and Important icons where appropriate, to point out safety-related, or other important information. The corresponding symbols should be interpreted as follows:



WARNING

The Warning icon indicates a potentially hazardous situation which, if not avoided, could result in death or serious injury, and major damage to the product.



CAUTION

The Caution icon indicates a potentially hazardous situation which, if not avoided, could result in minor or moderate injury, and moderate damage to the product.



NOTE

The Note icon alerts the reader to relevant facts and conditions.



IMPORTANT

The Important icon highlights important information.

2. Safety

Before using this product, please read this manual and other relevant manuals carefully. Pay full attention to safety instructions!

In no event will Beijer Electronics be responsible or liable for damages resulting from the use of this product.

The images, examples and diagrams in this manual are included for illustrative purposes. Because of the many variables and requirements associated with any particular installation, Beijer Electronics cannot take responsibility or liability for actual use based on the examples and diagrams.

2.1. Product Certifications

The product has the following product certifications.



2.2. General Safety Requirements



WARNING


- Do not assemble the products and wires with power connected to the system. Doing so cause an "arc flash", which can result in unexpected dangerous events (burns, fire, flying objects, blast pressure, sound blast, heat).
- Do not touch terminal blocks or IO modules when the system is running. Doing so may cause electric shock, short circuit or malfunction of the device.
- Never let external metallic objects touch the product when the system is running. Doing so may cause electric shock, short circuit or malfunction of the device.
- Do not place the product near inflammable material. Doing so may cause a fire.
- All wiring work should be performed by an electrical engineer.
- When handling the modules, ensure that all persons, the workplace and the packing are well grounded. Avoid touching conductive components, the modules contain electronic components that may be destroyed by electrostatic discharge.



CAUTION

- Never use the product in environments with temperature over 60°C. Avoid placing the product in direct sunlight.
- Never use the product in environments with over 90% humidity.
- Always use the product in environments with pollution degree 1 or 2.
- Use standard cables for wiring.

3. About the G-series System




System overview

- **Network Adapter Module** - The network adapter module forms the link between the field bus and the field devices with the expansion modules. The connection to different field bus systems can be established by each of the corresponding network adapter module, e.g., for MODBUS TCP, Ethernet IP, EtherCAT, PROFINET, CC-Link IE Field, PROFIBUS, CANopen, DeviceNet, CC-Link, MODBUS/Serial etc.
- **Expansion Module** - Expansion module types: Digital IO, Analog IO, and Special modules.
- **Messaging** - The system uses two types of messaging: Service messaging and IO messaging.

3.1. IO Process Data Mapping

An expansion module has three types of data: IO data, configuration parameter, and memory register. The data exchange between the network adapter and the expansion modules is made via IO process image data by internal protocol.



Data flow between network adapter (63 slots) and expansion modules

The input and output image data depend on the slot position and the data type of the expansion slot. The ordering of input and output process image data is based on the expansion slot position. Calculations for this arrangement are included in the manuals for network adapter and programmable IO modules.

Valid parameter data depends on the modules in use. For example, analog modules have settings of either 0-20 mA or 4-20 mA, and temperature modules have settings such as PT100, PT200, and PT500. The documentation for each module provides a description of the parameter data.

4. Specifications


4.1. Environmental Specifications

Operating temperature	-20°C - 60°C
UL temperature	-20°C - 60°C
Storage temperature	-40°C - 85°C
Relative humidity	5% - 90% non-condensing
Mounting	DIN rail
Shock operating	IEC 60068-2-27 (15G)
Vibration resistance	IEC 60068-2-6 (4 g)
Industrial emissions	EN 61000-6-4: 2019
Industrial immunity	EN 61000-6-2: 2019
Installation position	Vertical and horizontal
Product certifications	CE, FCC, UL, cUL

4.2. General Specification

Power dissipation	Max. 30 mA @ 5 VDC
Isolation	I/O to logic: Isolation Field power: Non-isolation
UL field power	Supply voltage: 24 VDC nominal, class2
Field power	Supply voltage: 24 VDC nominal Voltage range: 18-26.4 VDC Power dissipation: Max. 30 mA @ 24 VDC
Wiring	Connector type, up to AWG22 Module connector: HIF3BA-20D-2.54DSA
Weight	58 g
Module size	12 mm x 99 mm x 70 mm

4.2.1. Dimensions




Module dimensions (mm)

4.3. Input Specifications

Inputs per module	16 channels single ended, non-isolated between channel
Indicators	1 green G-bus status
Resolution in ranges	16 bit (include sign) 15 bits: 0.31 mV/bit (0-10 V), 0.15 mV/bit (0-5 V), 0.12 mV/bit (1-5 VDC)
Input current range	0-10 VDC, 0-5 VDC, 1-5 VDC
Data format	16 bits integer (2' compliment)
Module error	±0.1 % full scale @ 25 °C ambient ±0.3 % full scale @ -40 - 60 °C
Input impedance	500 kΩ
Diagnostic	Diagnostic field power off: LED blinking
Conversion time	1.5 msec / All channels
Field calibration	Not required
Common type	4 common, field power 0 V is common (AGND)

5. Wiring Diagram



Pin no.	Signal Description
0	Output channel 0
1	Output channel 1
2	Output channel 2
3	Output channel 3
4	Output channel 4
5	Output channel 5
6	Output channel 6
7	Output channel 7
8	Output channel 8
9	Output channel 9
10	Output channel 10
11	Output channel 11
12	Output channel 12
13	Output channel 13
14	Output channel 14
15	Output channel 15
16	Input channel common (AGND)

Pin no.	Signal Description
17	Input channel common (AGND)
18	Input channel common (AGND)
19	Input channel common (AGND)

6. LED Indicator



LED no.	LED function / description	LED color
0	Status LED	Green


6.1. LED Channel Status

Status	LED	Indicates
G-bus status	Off Green	Disconnection Connection
Field power error	Status channel repeat the Green and Off	Field power is not connected

7. Data value / Voltage


Voltage range: 0-10 VDC

Voltage	0.0 V	2.5 V	5.0 V	10.0 V
Data (Hex)	H0000	H1FFF	H3FFF	H7FFF




Voltage range: 0-5 VDC

Voltage	0.0 V	1.25 V	2.5 V	5.0 V
Data (Hex)	H0000	H1FFF	H3FFF	H7FFF



Voltage range: 1-5 VDC

Voltage	1.0 V	2.0 V	3.0 V	5.0 V
Data (Hex)	H0000	H1FFF	H3FFF	H7FFF



8. Mapping Data into the Image Table

Input Module Data

Analog input Ch 0
Analog input Ch 1
Analog input Ch 2
Analog input Ch 3
Analog input Ch 4
Analog input Ch 5
Analog input Ch 6
Analog input Ch 7
Analog input Ch 8
Analog input Ch 9
Analog input Ch 10
Analog input Ch 11
Analog input Ch 12
Analog input Ch 13
Analog input Ch 14
Analog input Ch 15



Input Image Value

Bit no.	Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0
Byte 0	Analog input Ch 0 low byte							
Byte 1	Analog input Ch 0 high byte							
Byte 2	Analog input Ch 1 low byte							
Byte 3	Analog input Ch 1 high byte							
Byte 4	Analog input Ch 2 low byte							
Byte 5	Analog input Ch 2 high byte							
Byte 6	Analog input Ch 3 low byte							
Byte 7	Analog input Ch 3 high byte							
Byte 8	Analog input Ch 4 low byte							
Byte 9	Analog input Ch 4 high byte							
Byte 10	Analog input Ch 5 low byte							
Byte 11	Analog input Ch 5 high byte							
Byte 12	Analog input Ch 6 low byte							
Byte 13	Analog input Ch 6 high byte							

Bit no.	Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0
Byte 14	Analog input Ch 7 low byte							
Byte 15	Analog input Ch 7 high byte							
Byte 16	Analog input Ch 8 low byte							
Byte 17	Analog input Ch 8 high byte							
Byte 18	Analog input Ch 9 low byte							
Byte 19	Analog input Ch 9 high byte							
Byte 20	Analog input Ch 10 low byte							
Byte 21	Analog input Ch 10 high byte							
Byte 22	Analog input Ch 11 low byte							
Byte 23	Analog input Ch 11 high byte							
Byte 24	Analog input Ch 12 low byte							
Byte 25	Analog input Ch 12 high byte							
Byte 26	Analog input Ch 13 low byte							
Byte 27	Analog input Ch 13 high byte							
Byte 28	Analog input Ch 14 low byte							
Byte 29	Analog input Ch 14 high byte							
Byte 30	Analog input Ch 15 low byte							
Byte 31	Analog input Ch 15 high byte							

9. Parameter Data

Valid parameter length: 18 Bytes

Bit no.	Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0
Byte 0	Voltage range for Ch 0 (H00: 0-10 VDC, H01: 0-5 VDC, H02: 1-5 VDC)							
Byte 1	Voltage range for Ch 1 (H00: 0-10 VDC, H01: 0-5 VDC, H02: 1-5 VDC)							
Byte 2	Voltage range for Ch 2 (H00: 0-10 VDC, H01: 0-5 VDC, H02: 1-5 VDC)							
Byte 3	Voltage range for Ch 3 (H00: 0-10 VDC, H01: 0-5 VDC, H02: 1-5 VDC)							
Byte 4	Voltage range for Ch 4 (H00: 0-10 VDC, H01: 0-5 VDC, H02: 1-5 VDC)							
Byte 5	Voltage range for Ch 5 (H00: 0-10 VDC, H01: 0-5 VDC, H02: 1-5 VDC)							
Byte 6	Voltage range for Ch 6 (H00: 0-10 VDC, H01: 0-5 VDC, H02: 1-5 VDC)							
Byte 7	Voltage range for Ch 7 (H00: 0-10 VDC, H01: 0-5 VDC, H02: 1-5 VDC)							
Byte 8	Voltage range for Ch 8 (H00: 0-10 VDC, H01: 0-5 VDC, H02: 1-5 VDC)							
Byte 9	Voltage range for Ch 9 (H00: 0-10 VDC, H01: 0-5 VDC, H02: 1-5 VDC)							
Byte 10	Voltage range for Ch 10 (H00: 0-10 VDC, H01: 0-5 VDC, H02: 1-5 VDC)							
Byte 11	Voltage range for Ch 11 (H00: 0-10 VDC, H01: 0-5 VDC, H02: 1-5 VDC)							
Byte 12	Voltage range for Ch 12 (H00: 0-10 VDC, H01: 0-5 VDC, H02: 1-5 VDC)							
Byte 13	Voltage range for Ch 13 (H00: 0-10 VDC, H01: 0-5 VDC, H02: 1-5 VDC)							
Byte 14	Voltage range for Ch 14 (H00: 0-10 VDC, H01: 0-5 VDC, H02: 1-5 VDC)							
Byte 15	Voltage range for Ch 15 (H00: 0-10 VDC, H01: 0-5 VDC, H02: 1-5 VDC)							
Byte 16	Filter time (H00: Default filter (20) / H01: Fastest / H3E: Slowest)							
Byte 17	Not used							Filter ON/OFF *

* Soft filter ON/OFF Setting - 0: Filter ON (Default) / 1: Filter OFF

10. Hardware Setup



CAUTION

- Always read this chapter before installing the module!
- Hot surface! The surface of the housing can become hot during operation. If the device is used in high ambient temperatures, always let the device cool down before touching it.
- Working on energized devices can damage the equipment! Always turn off the power supply before working on the device.


10.1. Space Requirements

The following drawings show the space requirements when installing the G-series modules. The spacing creates space for ventilation, and prevents conducted electromagnetic interference from influencing the operation. Installation position is valid vertical and horizontal. The drawings are illustrative and may be out of proportion.




CAUTION

NOT following the space requirements may result in damaging the product.



Vertical and horizontal space requirements



Required distance to door

10.2. Mount Module to DIN Rail

The following chapters describe how to mount the module to the DIN rail.



CAUTION


The module must be fixed to the DIN rail with the locking levers.

10.2.1. Mount GL-9XXX or GT-XXXX Module


The following instructions apply to these module types:

- GL-9XXX
- GT-1XXX
- GT-2XXX
- GT-3XXX
- GT-4XXX
- GT-5XXX
- GT-7XXX

GN-9XXX modules have three locking levers, one at the bottom and two on the side. For mounting instructions, refer to [Mount GN-9XXX Module](#).




Mount to DIN rail




Dismount from DIN rail

10.2.2. Mount GN-9XXX Module

To mount or dismount a network adapter or programmable IO module with the product name GN-9XXX, for example GN-9251 or GN-9371, see the following instructions:



Mount to DIN rail



Dismount from DIN rail


10.3. Field Power and Data Pins

Communication between the G-series network adapter and the expansion module, as well as system / field power supply of the bus modules is carried out via the internal bus. It is comprised of **2 Field Power Pins** and **6 Data Pins**.



WARNING

Do not touch the data and field power pins! Touching can result in soiling and damage by ESD noise.



Pin no.	Name	Description
P1	System VCC	System supply voltage (5 VDC)
P2	System GND	System ground
P3	Token output	Token output port of processor module
P4	Serial output	Transmitter output port of processor module
P5	Serial input	Receiver input port of processor module
P6	Reserved	Reserved for bypass token
P7	Field GND	Field ground
P8	Field VCC	Field supply voltage (24 VDC)

